

Denver SHA-150, Smart Alarm System

- Smart Home Alarm System with a keypad with back up lithium battery and built-in siren.
- Based on the TUYA platform - compatible with all other TUYA compatible models in the TUYA ecosystem.
- Uses TUYA SMART app
- The setup is compatible with Alexa & Google Assistant.
- Arm/Disarm the system by APP, SMS, phone call or via the keypad.
- Notifications in case of alert and system status changes.
- Stay connected through GSM even if you dont have an internet connection or your home Wi-Fi is offline.
- Audio surveillance of the site via the APP.
- Built-in siren in emergency cases.
- 600mAh/7.4V lithium battery included for more than 8 hours standby time.
- GSM module 850/900/1800/1900 MHZ
- 433 MHz wireless
- Can send alarm to 5 receivers by SMS/calling,1 speed-dial number and 1 RFID SMS notification number.

Accessories included

- 1 pcs. indoor IP cam with APP controlled motor (can move up/down via app)
- 1 pcs. wireless PIR sensor
- 1 pcs. wireless door sensor
- 1 pcs. remote controls
- 1 pcs. passive RFID tags
- 3 pcs. burglar preventive warning labels
- 1 pc. burglar preventive warning sign



-  Highlights
Wi-Fi Alarmsystem, GSM, 433MHz wireless sensors,
easy to setup and control by app or SMS, RFID tags,
Tuya compatible
-  Power
230V~50Hz AC/DC adaptor
-  Battery
Built-in rechargeable battery if power is lost
-  WIFI
Built-in Wi-Fi function
-  Connections
Simcard input, DC input

Shipping information

Unit size: 10.90(w) x 10.90(d) x 4.10(h) cm

Gross weight: 0.219

Giftbox size: 31.00(w) x 27.20(d) x 9.00(h) cm

4 Pcs./export carton

1710 Pcs./20' container

4400 Pcs./40' HQ container

Barcode: 5706751047169