

Denver BSS-10610

- Balcony Solar System with 2 x solar panels, Micro on-grid inverter, necessary cables
- Very easy setup and use. Connect it all, and then plug the Schuko plug into a power outlet In your home, and the solar system will send power into your electrical system
- Wi-Fi module built-in – for real-time monitoring on Smartphone & PC
- Each solar panel has a max power capacity on 330W/11A
- Panel material composition: Glass (surface) + EVA material + Solcar Cells + EVA materia + TPT film (backsheet)
- Panel type: Monocrystalline cells with PERC (Passivated Emitter and Rear Cell) + half cells tech
- Inverter has a max input on 600W max and is IP67 waterproof
- 2 x MPPT in inverter
- Output power: 230V and up to 2,5Aa.c.
- Standards: VDE 0126-1-1, VDE-AR-N 4105
- 10m Schuko power cable included

For installation + setup video (in German Language), please click here

[Denver BSS-10610 Balcony Solar System](#)

General security update for hiding Wi-Fi code (instructions are in the file)

[DENVER BSS-10600_10610 inverter upgrade.zip <-- Link](#)


Each set is 2 boxes. Measures of both units and boxes are below:




SOP-10600 (the 2 x solar panels) 158 x 104,50 x 3,5 cm (each)

Cardboard box they come in: 159,50 x 106 x 8 cm

SMI-601 (the inverter) 27,6 x 5,3 x 42 cm

Cardboard box they come in: 44 x 9,5 x 42 cm



-  Highlights
Solar panels, inverter, up to 600W, 2 x 330W solar panels, plug into existing electrical system
-  Power
Can give up to 600W power to your electrical system (depending on how much sun there is)
-  WIFI
Built-in Wi-Fi function for live view of power

Shipping information

Unit size: 0.00(w) x 0.00(d) x 0.00(h) cm

Gross weight: 42.35

Giftbox size: 0.00(w) x 0.00(d) x 0.00(h) cm

1 Pcs./export carton

0 Pcs./20' container

350 Pcs./40' HQ container