

Denver WCM-8010MK3

- Digital wildlife camera with 8mp CMOS
- Built-in 2.0" LCD screen
- 8mp cmos image sensor (5/8/12MP image res.)
- 2G/GSM Simcard reader - insert nano simcard & receive pictures via MMS and/or Email
- 3 motion sensors
- Full automatic ir filter for use in the dark - 42 leds
- Lens: F=3.09; F/NO=2.0; FOV 90°
- Pir sensing distance: 1-25 meters
- Trigger speed 0,3 second
- Standby time: up to 3 months
- MicroSD card slot for rec. - up to 32gb (card not included)
- Video resolution: 1080p,
720p, vga (up to 1440x1080)
- Waterproof: ip65 standard

You can download MMSCONFIG program here:

[MMSCONFIG](#)





You can find a guide on how to setup your camera here:

<https://denver-electronics.com/media/27816/this-is-how-you-setup-your-wcm.pdf>

If using SMTP mode and Gmail, you need to use following settings (because of Google's new email demands)

[Gmail SMTP setting.pdf](#)

[Gmail settings - Italian](#)

-  Highlights
Wildlife cam, MMS function, 8mpixel CMOS sensor, full automatic IR light with 42 LED's, IP-65 waterproof
-  Battery
Uses 8 x size "AA" batteries (not included)
-  Camera
8Mpixel CMOS sensor, 90° fixed angle
-  Connections
TV out, USB-C, MicroSD card input, simcard input

Shipping information

Unit size: 9.50(w) x 8.20(d) x 13.50(h) cm

Gross weight: 0.6

Giftbox size: 16.80(w) x 12.30(d) x 11.00(h) cm

4 Pcs./export carton

10000 Pcs./20' container

24400 Pcs./40' HQ container

Barcode: 5706751039416